



3700 Running Watts*
4500 Starting Watts**



| | |
|--------------------------------|------------------------|
| Model | P4500 |
| Part Number | 030807 |
| Number Of Outlets | 3 |
| Engine | Briggs & Stratton® OHV |
| Displacement | 224cc |
| Amperage | 15A |
| Voltage | 230V AC |
| Auto Idle | Yes |
| Auto Voltage Regulation | Inverter |

| | |
|----------------------------------|---------------------------------------|
| Fuel Tank Capacity (L) | 13.2 |
| Muffler | Yes - Spark Arrestor Type |
| Weight (Kg) | 47 |
| Low Oil Protection System | Yes |
| RCD | No |
| Dimensions L x W x H (cm) | 62.2 x 44.7 x 51.6 |
| Warranty Consumer | 3 Years Limited Warranty ¹ |
| Warranty Commercial | 1 Year Limited Warranty ¹ |

- COGuard - Shuts down your generator when harmful levels of carbon monoxide are detected
- QPT™ Quiet Power Technology - Automatically adjusts the engine speed further reducing noise and fuel consumption
- Easy Portability with telescopic handle along with side hold handles and integrated wheels

- The PowerSmart Series Inverter Generators deliver 'pure sine waves' at 4500 watts peak and 3700 watts continuous which makes it ideal for sensitive electronic equipment
- Electric Push Button Start and Remote
- Statstation™ Digital Display - Displays power usage, total unit lifetime hours, and maintenance reminders.
- Up to 16 hours run time @ 25% load

* Per CSA C22.2 No. 100-14 and ANSI/PGMA G300-2018

** Starting Watts is the maximum current that can momentarily be supplied when starting a motor, multiplied by the generator's rated voltage.

¹ See www.briggsandstratton.com for warranty details.

Briggs & Stratton has a policy of continuous product improvement and reserves the right to modify its specifications at any time and without prior notice. Product may vary from images shown.