





Jackery Explorer 1000 Pro



-  Refrigerator
1.6H (520W)
-  Coffee Maker
1.5H (550W)
-  Hair Dryer
0.9H (1000W)
-  Electric Blanket
14H (55W)
-  Microwave
1.2H (700W)
-  Kettle
1H (850W)
-  Instant Pot
0.9H (1000W)
-  TV
13H (60W)

SPECIFICATION		WHAT'S IN THE BOX
Capacity	1002Wh	 1* Explorer 1000 Pro Portable Power Station (1002Wh)
Continuous Output	1000W	
Peak Output	2000W	
Charged with AC Adapter	Li-ion NCM	
Charged with 12V Car Outlet	After 1000 cycles, ≥ 80% capacity remains	
Charged with Solar Panel	25.35lbs(11.5KG)	
Battery Lifecycles	13.39 x 10.32 x 10.06in(34 x 26.2 x 25.5cm)	
Output Ports	AC Outputs (* 2): 230V,50Hz,4.34A, 1000W Rated(2000W Surge peak) USB-A outputs(×2):Quick Charge 3.0, 18W Max 5-6V/3A,6-9V/2A,9-12V/1.5A USB-C Outputs(×2):100W Max 5V/3A, 9V/3A, 12V/3A, 15V/3A, 20V/5A Car Port(×1):12V/10A	 1* Car Charge Cable
Input Ports	AC Input: 230V, 50Hz, 10A Max DC Input:12V-17.5V/8A, Double to 16A Max , 17.5V-60V/11A, Double to 22A/800W Max	 1* AC Charge Cable
PACKAGE		 1* User Manual
Box Size	16.4x12.2x14.8in (41.8x31.1x37.6cm)	
Weight with Box	45.08lbs (20.45kg)	
Qty/ Carton	1pcs/carton	
GW	50.19lbs (22.77kg)	
Carton Size	17.2x12.9x15.5in (43.8x32.8x39.6cm)	
RECHARGING TIME TO 100%		
Charged with AC Adapter	1.8 Hours	
Charged with 12V Car Outlet	12 Hours	
Charged with Solar Panel	7 Hours (6*200W Panels)	
RECOMMENDED COMBO		



1* Explorer 2000 Pro + 2*SolarSaga 80



1* Explorer 2000 Pro + 2*SolarSaga 100